




	EZCast Pro Series		QuattroPod Series
	EZCast Pro Dongle II 	EZCast Pro Box II 	QuattroPod Lite 
Recommended for	Small meeting rooms	All meeting rooms	All meeting rooms
Maximum Resolution	4K / 30fps	4K / 30fps	4K / 30fps 1920 x 1080 Pixel / 60 fps via transmitter, 3840 x 2160 Pixel / 30 fps via Apple Airplay and Chromecast
App / Software required for complete functionality	Yes	Yes	No
Receiver / Transmitter Interface	Software	Software	Hardware Transmitter / Software
Max. number of transmitters	32	32	1
CPU	AM8270	AM8270	AM8270
DRAM (for QuattroPod Lite: Receiver / Transmitter)	DDR3 1 GB	DDR3 1 GB	DDR3 512 MB / 256 MB
Power Supply (for QuattroPod Lite: Receiver / Transmitter)	DC-in 5V 1.5A	DC-in 5V 2A	DC-in 5V 2A / DC-in 5V 0,9A
USB Charger included	No*	Yes	Yes
Operating Systems: Windows / macOS / iOS / Android	Yes	Yes	Yes
Compatible with any display or projector	Yes	Yes	Yes
Touch Back Support	No	Yes (only via EZCast Pro Software)	Yes (without Software)
ProCast (broadcast to up to 8 projectors / displays simultaneously)	Yes	Yes	No
Castcode pin security	Yes	Yes	No
Wi-Fi Standard	5 GHz 802.11ac 2T2R single band 866 MBit/s authentication protocol WPA2-PSK	5 GHz 802.11ac 2T2R single band 866 MBit/s authentication protocol WPA2-PSK	5 GHz 802.11ac 2T2R single band 866 MBit/s authentication protocol WPA2-PSK
LAN	No	1 GBit/s	No
PoE	No	Yes	No
Simultaneous Casting (Split Screen up to 4 screens)	Yes	Yes	No
BYOD support without additional app/software for Apple AirPlay, Chromecast and Miracast	Yes	Yes	Yes**
EZCast Pro App for Android	Yes	Yes	No
EZCast Pro App for iOS	Yes	Yes	No
EZCast Pro Software for Windows / macOS	Yes	Yes	No
AirView via EZCast Pro Software (broadcast to up to 64 device a picture every 5 sec.)	Yes	Yes	No
Moderator (Host) Control	Yes	Yes	No
Dimensions in mm (W x D x H) (for QuattroPod Lite: Receiver / Transmitter)	87,5 x 32 x 12 (without HDMI port)	120 x 80 x 25 (without antenna)	120 x 80 x 25 (without antenna) / 61 x 61 x 23 (without antenna)
Weight in g without accessories (for QuattroPod Lite: Receiver / Transmitter)	30	146	107 / 53
Manufacturer	Winner Wave Limited, Taiwan		

Product Comparison
EZCast Pro Series


* Sold seperately

** Miracast is not supported on this device. Free QuattroPod App available.

© STÜBER SYSTEMS GmbH, Updated: August 2020

STÜBER SYSTEMS GmbH
Grabbeallee 31
D-13156 Berlin
Germany
+49-30-23256-1900
hello@stueber.de
www.ezcastpro.eu